

DATA GENERAL CORPORATION

SOUTHBORO, MASSACHUSETTS 01772

SIZE A	CODE 008	DWG NO. 000-075	REV 02
TITLE Line Printer Internal Cable Nova 800/1200 Only			

ORIGINATOR: K. Clapp	DATE 2/71	MODEL NO. 4034	NEXT ASSY	CODE 005	DWG NO. 000-384	REV 01
ENG:	CHECKED BY:	APP BY:	SCHEMATIC REF NO.			

REV NO.	ECO NO.	APP BY	DATE	PAGE NO'S	26 AWG USED UNLESS OTHERWISE SPEC Solid
01	295	KC	4/71	1 & 2	NOTES 1. 25S Connector Pins (From) 2. Back Panel Pins (To) 3. 4. 5. Tag Loose Wires with Back Panel Pin Location 6. Returns on Pin 2,4,6,8,10 are to be 26AWG Stranded Wire 2" long Splice these wires to 1. Blu 26 AWG Solid Wire & Run it to B-1 7. Returns on Pins 12,14,16,18,20,24, same as above, Run solid wire to B-99
02	458		7/71	1 & 2	

ITEM NO.	FROM	SIGNAL NAME	TO	FUNCTION	COLOR	LENGTH	AWG
1	1	RDY	B-19		Wht.	18"	26
2	2	RTN			Blk.	2	26
3	3	Demand	B-23		Wht.	18"	26
4	4	RTN			Blk.	2	26
5	5	Strobe	B-25		Wht.	18"	26
6	6	RTN			Blk.	2	26
7	7	Data 1	B52		Wht.	18"	26
8	8	RTN			Blk.	2	26
9	9	Data 2	B-49		Wht.	18"	26
10	10	RTN			Blk.	2	26
11	11	Data 3	B-48		Wht.	18"	26
12	12	RTN			Blk.	2	26
13	13	Data 4	B-51		Wht.	18"	26
14	14	RTN			Blk.	2	26

